



## Preston Communication Compatibility Chart

Generation	Preston Units	# of channels	Comments
 <p><b>G4 Blue Dot</b></p>	MDR-3 MDR-2 VLC HU-3 Focus Iris Radio Microforce	1-59	<p>G4 units can be sent in for a <b>free blue dot upgrade</b>. For fastest turnaround please contact us to schedule this procedure.</p> <p>Any receiver (MDR or VLC) + controller (Focus/Iris, HU3) pair must <b>BOTH</b> be blue dot upgraded in order to use channels 30 - 59.</p> <p>These additional channels are encoded for <b>better interference rejection</b>. For best interference rejection use channels 30 and 59. For longest range use channel 45.</p> <p><b>G4 Blue Dot units are backwards compatible with all G4 units on channels 1-29</b></p>
 <p><b>G4</b></p>	MDR-2 VLC HU-3 Focus Iris Radio Microforce  <i>Fx Box - *cannot be blue dot upgraded*</i>	1-29	<p><b>G4 upgrade</b> can be performed from G3 (\$450 per unit) for <b>all units except</b> HU-2 with Transmitter II</p>
<p><b>↕ Not compatible</b></p>			
<p><b>G3</b></p>	HU-2 w/ Transmitter II - <i>*cannot be G4 upgraded*</i> MDR-2 w/ G3 board HU3 w/ G3 board VLC w/ G3 board Focus Iris w/ G3 board Radio Microforce w/ G3 FX box w/ G3 board	1-29	<p><b>No upgrades</b> can be performed for G2 units to work with G3 units.</p>